



- All service should be performed by qualified personnel - power supply to be disconnected prior to installation.
- Connections made must comply with local regulations and the national electrical code. Contact Solera for additional information on installations.

## Installation Instructions: CURVE-24

Make all the necessary power wire connections in the junction box.

Place the mtg. plate over the center of the junction box. Secure to the junction box with qty (2) screws, or the wall using lag screws, or both. (Hardware by others)

Position the fixture housing over the wall mtg. plate and use qty (6) screws (supplied) to secure housing to the wall mtg. plate.

**ADDITIONAL NOTES:**  
If mounting on walls with rough or uneven surfaces, silicone must be applied around the edges of the housing between wall and the fixture.

